

Flush Mount Key-switch

Art.-Nr. SE1100

Seite 1 von 2



Use the flush mount key-switch to arm and disarm your alarm system. Simply turn the key instead of entering a PIN code. Operating your system is faster and easier. Apart from the arm/disarm function of the alarm system (or individual partitions), you can use the flush mount key-switch to control electronic equipment (entrance lighting, garage door, etc.). Two switch contacts are provided. You can set these as a permanent contact or as a pulse generator. The two colored LEDs inform you permanently about the state of connected devices. For example, you can see if the system is currently armed or disarmed. The reinforced fascia plate, the high-quality ABUS cylinder and a robust weatherproof housing (IP 55) protect the key-switch against external influences. The flush mount key-switch is designed for half-cylinders (10/30). It is available for both surface and flush fitting. The surface-fitted variant is protected from tampering by a cover contact and an anti-removal wall contact.

Technologies

- Arm and disarm by turning the key
- For flush mounting
- High security with pull protection and ceiling tamper switch
- Sturdy housing

Technical data - Flush Mount Key-switch

Colour	white
Compatible with	Secoris, Secvest, Terxon
Current consumption	2 mA
DC power supply	10-15 V
Depth	42 mm
Dimensions	(WxHxD) 106x134x42 mm
Height	134 mm
Housing material	ABS

Flush Mount Key-switch

Art.-Nr. SE1100

Seite 2 von 2

Technical data - Flush Mount Key-switch

Length	42 mm
Mechanical protection	No
Mounting location	Flush fitting
Net weight	0.311 kg
Number of rooms / groups	1
PSTI conformity needed	No
Power consumption	0.02 W
Product group	Operation
Protection class IP	55
Status display	Yes (2 LEDs)
Tamper monitoring	Yes
Touchpanel	No
VdS class	without
WEEE group	09
width	106 mm