

# Smartvest Wireless Magnetic Contact

Art.-Nr. FUMK35000A

Seite 1 von 2



The Smartvest Wireless Opening Detector enables you to monitor windows and doors, while its battery operation makes it easy to install, avoiding the need for drilling or wiring. When the battery is low, the Smartvest Wireless Opening Detector sends an automatic notification to the alarm panel about this. The free Smartvest app then guides you step by step through the process of replacing the batteries. In combination with the Smartvest Wireless Socket, you can then initiate certain smart functions such as open door or light on, in addition to monitoring. Compact in size, the Smartvest Wireless Opening Detector is absolutely inconspicuous and blends discreetly into the interior of the room.

## Technologies

- Smartvest extension for monitoring doors and windows
- Quick and cable-free installation without the need for wires or drilling thanks to battery operation
- Tamper protection via cover contact
- Visual notification via blue LED when starting up and functioning
- Automatic supervision, with functional tests repeated daily and feedback sent to the Smartvest alarm control panel
- Low battery notification sent to the Smartvest alarm control panel
- Battery life of up to 1 year
- Small, discreet and secure

## Technical data - Smartvest Wireless Magnetic Contact

|                             |             |
|-----------------------------|-------------|
| Areas of application        | Interior    |
| Battery - battery operation | Yes         |
| Battery - max. battery life | 1 years(s)  |
| Battery - quantity          | 1           |
| Battery type                | CR2032 (3V) |
| Colour                      | white       |

# Smartvest Wireless Magnetic Contact

Art.-Nr. FUMK35000A

Seite 2 von 2

## Technical data - Smartvest Wireless Magnetic Contact

|                                   |                                        |
|-----------------------------------|----------------------------------------|
| Compatible with Secvest           | No                                     |
| Compatible with Smartvest         | Yes                                    |
| Current consumption               | 15 mA                                  |
| Current consumption standby       | 0.005 mA                               |
| Dimensions                        | (B x L x H) 40 x 14 x 71 mm            |
| Display type                      | LED                                    |
| Gross weight                      | 0.092 kg                               |
| Housing material                  | Plastic                                |
| Max. Air humidity                 | 80 %                                   |
| Max. Operating temperature        | 40 °C                                  |
| Min. humidity                     | 10                                     |
| Min. operating temperature        | 0 °C                                   |
| Net weight                        | 0.03 kg                                |
| PSTI conformity given             | No                                     |
| PSTI conformity needed            | Yes                                    |
| Product group                     | Detectors                              |
| Product security update min until | 2024-12-31                             |
| Radio frequency                   | 868 MHz                                |
| Radio modulation                  | FSK                                    |
| Radio networked                   | Yes                                    |
| Radio range                       | (Depending on installation) 30 - 100 m |
| Tamper protection                 | Yes                                    |
| Transmission power                | 4,5 dBm                                |
| VdS class                         | without                                |
| WEEE group                        | 09                                     |
| Width sensor                      | 14 mm                                  |